

Gavita Pro 1000^e DE US 208-240 SL



General product information

Product name:	Gavita Pro 1000 ^e DE US 208-240 SL
Manufacturer:	Gavita International bv
Version:	US 208 - 240 V SL
Part number:	18.30.14.24.20

Compatible products and accessories

	Product name	Gavita part number
Controllers:	Gavita Master Controller EL1	41.00.12.20
	Gavita Master Controller EL2	41.00.13.20
Reflectors:	Gavita Pro HR 96 DE reflector	30.46.13.00
	Gavita Pro W 150 DE reflector	31.26.13.00
	Gavita Pro MD 135 DE HC	30.07.13.00
Lamps:	Gavita Pro Plus 1000W EL DE HPS	26.10.16.12
Power cord:	Power cord US 240 V, 8.2 ft / 2,5 meter	44.30.41.10
Interconnect cables:	Interconnect cable RJ	43.50.00.17
	Repeater Bus connection kit	43.50.10.00

Technical specifications

Product name:	Gavita Pro 1000 ^e DE US 208 - 240 SL	
Input voltage +/- 10%:	208 volt AC	240 Volt AC
Frequency:	50 - 60 Hz	
Input current at 100%:	5.2 Amps	4.5 Amps
Input current at 115%:	5.9 Amps	5.1 Amps
Input power at 100%	1050 Watt	1050 Watt
Input power at 115%	1236 Watt	1236 Watt
Inrush current:	< 40 Amps	
Power factor:	0.97 - 0.99	
Product weight:	8.4 lbs (3,8 kg)	
Dimensions (LxWxH):	22.2"x9.7"x7.8" (56,5x24,5x19,5cm)	
Temperature ambient:	32-95 °F (0 - 35°C)	
Relative humidity:	<70%	
Total Harmonic Distortion:	<10%	
Power inlet:	IEC C14	
External dim connector	RJ connector built in (6p6c)	

Legislation

This device complies with c CSA us

Included accessories

User manual, power cord, Interconnect cable RJ14 5 ft and a T-splitter for plug and play installation, Gavita Pro 1000 lamp.